


CKC

V4



www.ckclighting.com

CKC LIGHTING CO.,LTD

Addr.:335 Nansha Avenue, Tung Chung Town,
Nansha District, Guangzhou City, China.
TEL: (020)3920 4506 FAX: (020)3920 4631
WEB: www.ckclighting.com



Before carrying out any installation, maintenance, or cleaning of the lighting fixtures, please confirm that the power has been cut off! Before using this fixture, please read this manual. Our company reserves the right to change product design and specifications without prior notice.

CONTENTS

1. Security Warning Information	1
2. Product Introduction	3
2.1 Exterior dimensions	3
2.2 Fixture packaging accessories	3
3. Main technical parameters of the equipment	3
4. Packaging and transportation	8
4.1 Disassemble packaging	8
4.2 Equipment installation	8
5. Installation Requirements Explanation	9
5.1 Clamp installation	9
5.2 Fixture installtion	10
5.3 Hanging Installation Diagram	10
6. Power and signal connection	11
6.1 Power and signal socket	11
6.2 Power Connect	11
6.3 Signal Connect	12
7. Control panel	12
7.1 Panel Introduction	12
7.2 System menu	13
8. DMX control channel table	15
9. Control circuit diagram	19
10. Regular maintenance	19
10.1 Cleaning and maintenance	19
10.2 Fault analysis and handling	20

★ Statement ★

- This manual contains important information on safe use and installation. Please read it carefully and follow the requirements for operation and installation. Please keep this manual properly;
- The equipment has good performance and complete packaging when it leaves the factory. The operator should strictly follow the warning items and operating instructions stated in the manual. Any malfunction or damage caused by misuse or neglect of the manual is not within the scope of our company's responsibility and warranty;
- The relevant information in this manual is for reference only. All lighting products are subject to the actual product. Any changes will not be notified separately, and our company reserves the right of final interpretation.

1. Security Warning Information



Attention !

Please read the safety requirements information in this section carefully before installing, powering on, operating, or repairing the lighting fixtures.



- This product is for professional use and is not suitable for other purposes;
- After receiving the lighting fixtures, please check if the packaging is complete and unpack to check if the equipment has been damaged due to transportation. If there is any damage caused by transportation, please do not use this lamp and contact local technicians or manufacturers as soon as possible;
- When transporting again, please use the original packaging materials;
- If there is obvious damage to the machine casing, it should be replaced in a timely manner;
- When hanging lamps, it is necessary to verify that the hanging equipment can withstand more than 6 times the weight of the lamp. After installation, it is necessary to verify that the lamp cover and installation buckle are secure and undamaged. At the same time, a safety rope should be used as an auxiliary safety for the lamp and fixed on the truss;
- The light source inside this luminaire should be replaced by the manufacturer, its service agent, or a similarly qualified person;
- If you have any other questions about how to safely operate the equipment, please contact our technical personnel or call our service hotline;
- This product has a protection level of IP20 and is suitable for indoor use;
- Avoid direct external strong light shining on the lens, which may cause the lens to focus and burn out internal components.



- Lighting fixtures should be kept clean and avoid prolonged use in overheated or dusty environments to prevent contact with chemical liquids;
- When using the product, attention should be paid to avoiding serious or fatal injuries caused by fire, heat, electrical shock, and ultraviolet radiation. Before powering on or installing, read the instruction manual first. Follow the safety precautions for operation and pay attention to the warning signs on the instructions and equipment;
- Only professionals are allowed to install, operate, and maintain lighting fixtures, and strictly follow the procedures stated in the operating instructions.



- The eyes cannot directly look at the luminous object;
- Do not connect this device to any dimmer;
- If visible damage occurs to the protective casing, lens, and display screen on the lighting fixture, it is considered as damage to the point of loss;
- Please do not place any filters or other items at the light outlet, and do not replace non original parts;
- The minimum safe illumination distance of the lamp is 3m.



- Before installation, please confirm that the power supply voltage used matches the voltage indicated on the light fixture. Each lighting fixture should be properly grounded and electrically installed according to relevant standards;
- Please disconnect the power before repairing or cleaning the equipment;
- During the operation of the lighting fixtures, touching the wires is prohibited to prevent electric shock;
- If the external soft cable or wire of this lamp is damaged, the wire should be replaced by the manufacturer, its agent, or a similarly qualified person to avoid danger;
- Avoid flammable liquids, water, or metal conductors from entering the interior of the lamp to prevent electric shock or fire. If any foreign objects enter the lamp, immediately cut off the power supply;
- When multiple lamps are operated in series, the signal lines can be connected in multiple ways, but the power supply must be connected separately.




- The lighting fixtures work normally at -20 °C to 45 °C . When replacing any components or accessories in the equipment, ensure that the power is disconnected to prevent electric shock and injury;
- The maximum surface temperature of the lamp during operation can reach 68 °C , please do not touch it with bare hands.



- The lighting fixtures must be installed in a sufficiently ventilated area, at least 0.5m away from adjacent surfaces, to ensure that no ventilation holes are blocked;
- Do not install the lighting fixtures directly on flammable objects;
- The minimum distance between all outer surfaces of the lamp and combustible materials is 0.5m.


2. Product Introduction

2.1 Exterior dimensions of lighting fixtures



2.2 Packaging accessories

Name	QTY
Omega bracket	2 PCS
Clamp	2 PCS
Safety cable	1 PCS



3. Main technical parameters of the equipment

Product execution standards: GB7000.1-2015, GB7000.217-2008, Q/YF 1-2017

● Electrical parameter

Rated input voltage: AC 100V-240V~ 50Hz/60Hz
 Rated power of the entire fixture: 660W
 Power factor: 0.997F
 Input Current: 2.586A 220V

● Source lifespan



>20000 hours

● Optical system

LED source: 350W CW LED
 Beam angel: 3 ~ 53°
 Output luminous flux: 15000 Lm


● Color system

CCT: 6800K
 CRI: 70 (With CRI filter)
 Color wheel: 8+1
 CMY+CTO




● Gobo system

Gobo outer diameter: 16.5mm ± 0.2 mm Internal diameter: 11.5mm
 Thickness: 1.1mm




Gobo replace


1. Unscrew the two screws at location **A**, unplug the power cord at location **B**, and take out the Gobo component;




2. As shown in **C**, gently lift the driven wheel from the edge upwards from the front of the pattern plate and slowly pull it out to remove a single pattern seat;




3. Use tweezers or other small grippers to remove the snap spring at point **D** (If the pattern piece is coated with glass glue for fixation, please use a professional cleaning agent to remove the glass glue before removing the snap spring to avoid damaging the gobo);



4. When assembling the Gobo, avoid touching it directly with your hands. Align the location of the Gobo's positioning point **E** with the positioning point **F** on the back of the driven wheel component (the coating surface of the Gobo should face the light source), and install the snap spring;




5. Insert the Gobo holder into the drive wheel assembly and reinstall it in the order it was removed; The positioning point **F** of the Gobo holder should be aligned with the positioning point **G** of the driving wheel; after installation, simply reinstall the Gobo holder component onto the fixture.




● Framing system

4 gratings achieve fast and smooth cutting, and the cutting direction and angle of each grating can be controlled separately. The single grating can achieve complete light closure, and the entire frame module can rotate $\pm 60^\circ$




● Animation



● Prism system

8 prism+ 6 linear




● Pan/Tilt

Pan scan:

540° or 630° 8-bit/16bitrecision scanning

Tilt scan:

270° 8-bit/16bit precision scanning



● Control and programming

Control channel: 38CH/52CH

Protocol: DMX512, RDM

Data connect: 3 pin signal in/out , 5 pin signal in/out

● Illumination draw

3°	5	8	10	12
Lux	84100	32900	21200	14900
Distance(m)	0.26	0.42	0.52	0.63

53°	5	8	10	12
Lux	1000	443	310	204
Distance(m)	4.99	7.98	9.97	11.97

● Other effect function

Fast electronic strobe: 1~25Hz

LED refresh frequency: 900Hz-25KHz

Frost: Light frost+heavy frost
Iris

● Other features and functions

Weight: 22 KG

Carton size: 79 × 49.5 × 43.5 cm

N.W: 28.6 KG

4. Packaging and transportation

4.1 Disassemble packaging



Notice: After receiving the fixture, please unpack and check for any damage caused by transportation. If there is any damage caused by transportation, please do not use this fixture and contact the local technical personnel or manufacturer as soon as possible.


4.2 Equipment packaging

- 1). Disconnect the power supply before packaging the lighting fixtures to allow them to cool completely;
- 2). Flight cases can only be stacked in two layers and are not allowed to be reversed.

5. Installation Requirements Explanation

5.1 Clamp install



The lighting fixtures can be installed on the stage or on any direction of the truss, and the clamp can be quickly and easily locked onto the truss.



Warning !

The lighting fixtures are divided into two versions: integrated light hook and normal. When using the integrated light hook version, the clamp is broken up and locked onto the truss. The normal version must use 2 clamps to secure the device and fasten it with a 1/4 rotation. Regardless of the version, one safety rope must be added and connected to the base hole, but be careful not to connect it to the handling handle.


Quick lock and clamp install



5.2 Equipment installation

- 1). Before installation, it is necessary to verify that the lamp hook and safety rope are not damaged, and that the installation object can withstand 6 times the total weight of the lamp and cable accessories;
- 2). Install the quick lock clamp on the base of the lamp body. Insert the clamp horizontally into the mounting hole of the base, rotate it clockwise 1/4 turn to lock it, and install the second clamp using the same method (the shape of the clamp should be based on the actual product).


5.3 Hanging Installation Diagram



Reminder: External beam source may damage internal lighting fixtures

External beams from direct sunlight, lighting fixtures, and lasers that are directly focused onto the casing or penetrate the lens to illuminate the interior of the fixture may cause damage to the components. This is a common issue with all lighting fixtures and does not occur alone with CKC products. Although there is no way to completely prevent this problem from occurring, following the following guidelines can prevent potential damage.


When unpacking, installing, using, and stopping the operation of the lighting fixtures, please do not expose the transparency of the fixtures the mirror is exposed to direct sunlight, other lighting fixtures, or laser beams. Do not directly focus the beam of this device onto another lighting fixture.




6. Power、Signal connect

6.1 Power and signal socket

- 1.Fuse holder
- 2.Power input
- 3.Power output
- 4.3 Pin DMX input
- 5.5 Pin DMX input
- 6.3 Pin DMX output
- 7.5 Pin DMX output



6.2 Power connect



Power In

Connection method:

L(live wire) - brown wire

E(Ground wire) - yellow/green dual color line

N(Zero Line) - Blue Line

When connecting the power supply, please note that the voltage and frequency of the power supply must match the voltage and frequency marked on the light fixture. When multiple fixtures are used simultaneously, it is recommended to connect the power supply of each fixture separately, so that each fixture can be individually controlled for power on/off.



Attention: When connecting the power supply, the ground wire (yellow/green dual color wire) must be safely grounded and comply with all relevant electrical installation standards.


This product uses Powercon In/Out to connect power cable. Due to power limitations, a 2mm power cable can drive up to 1 fixtures at 220V.




Warning !

- Do not connect too many fixtures or overload a single power cord;
- Do not use power cords with damaged insulation layers, and do not place power cords on other wires;
- When the fixture is not in use or cleaned, please unplug the power cord; Do not forcefully unplug or drag the power cord directly.


6.3 Signal connect



The lighting fixtures are equipped with standard DMX XLR input and output sockets. Please use DMX512 shielded twisted pair signal cables or Category 5 or above network twisted pair cables for connection. The typical connection distance for DMX signal lines is 150 meters. When transmitting signals over long distances, a DMX512 signal amplifier must be added.




Connect a shielded twisted pair signal cable from the DMX output port of the controller to the DMX input port of the first device, and from the DMX output port of the first device to the DMX input port of the second device, and so on, until all the lamps are connected. Then install a terminal plug on the last 3 pin socket of each connected lamp output. (Weld a 4/1W, 120 Ω resistor between the 2 and 3 pins of a 3 or 5 core pin XLR plug).



7. Control panel

7.1 Panel Introduction



● Adopting a 1.8 "LCD display screen, the operation panel is equipped with a rechargeable battery, which can enter the menu to set address codes and make other settings without powering on;

● Press the MODE key to view or modify the lighting function settings, and press the UP, DOWN, LEFT, and RIGHT keys to select the function menu;

● Press the ENTER key to confirm your selected function menu, which will take you to the corresponding sub menu in the menu. Each menu item represents a specific function of the lighting fixture (as shown in the table below);

● Press the ENTER key to save your modifications or enter a submenu, and press the UP or DOWN key to modify values (increase or decrease values); Press the MODE key to return to the previous menu or exit.

● Press the MODE key to return to the previous menu or exit.

7.2、System menu

Note: The gray color block is the default setting value

Software Update
Please Wait...
CKC
V4
Temperature Check
LED Temp xxxC
Base Temp xxxC
Motor Reset
Please Wait...

Receive	Set Address	A001-XXX	
User Mode	User Mode	Standard (16bit)	
		Extend	
		User A	
User B			
		User C	
	Edit A	Max Channel	
	Edit B	PAN	
	Edit C	:	
	Status	No DMX Mode	Black/ Hold/ Auto
		P.Reverse	ON/OFF
		T. Reverse	ON/OFF
		Pan Degree	630/540
		Feedback	ON/OFF
		Move.Speed	Speed 1~ 4
		Hibernation	OFF, 01M~99M
	Dim Mode	Standard	
Stage			
TV			
Architectur			
		Theatre	

Function	Temp. C/F	Celsius Fahrenheit
	Dim Curve	Linear/Square /I-Square/S-Curve
	Frequency	900Hz/1000Hz/1100Hz/1200Hz/1300Hz/1400Hz/1500Hz/2500Hz/4000Hz/5000Hz/10KHz/15KHz/20KHz/25KHz
	Fan.Set	Head Fan Auto Silent High
	LCD.Set	Backlight 02~60m <05m> Flip Display ON/OFF Key Lock ON/OFF DispFlash ON/OFF
	Disp.Set	Chan.Value PAN..... Slave Set Slave1,Slave2 Auto.Prog Master / Alone
	DFSE	ON/OFF
	USB Update	OFF/ON
Info	Time.Info	Current Time (Hours) Total Time (Hours) Last Time (Hours) Timer PIN (Password=050) Clear Last (ON/OFF)
	Temp. Info	Head: xxxF/C Base: xxxF/C
	Fan Speed	LED :xxxxRPM Gobo :xxxxRPM Head :xxxxRPM Base :xxxxRPM
	Error. Info	Pan,Tilt.....
	Model. Info	V4
	Software.V	1U:V1.x.x 2U:V1.x.x 3U:V1.x.x 4U:V1.x.x 5U:V1.x.x 6U:V1.x.x 7U:V1.x.x 8U:V1.x.x
Test	Reset.Motor	A11/Pan&Tilt/Head
	Test.Channel	PAN
	Panel.Ctrl.	PAN =XXX :
	Calibrate	-Password-(050) PAN、Tilt...

8. DMX channel table:

38CH	52CH	Function	Values
1	1	Pan	000 - 255 0% to 100%
2	2	Pan fine	000 - 255 0% to 100%
3	3	Tilt	000 - 255 0% to 100%
4	4	Tilt fine	000 - 255 0% to 100%
5	5	Dimmer	000 - 255 0% to 100%
6	6	Dimmer fine	000 - 255 0% to 100%
7	7	Strobe	000 - 031 No function (shutter closed)
			032 - 063 No action, shutter open
			064 - 095 Strobe slow to fast
			096 - 127 No action, shutter open
			128 - 159 Slow to fast pulse effect
			160 - 191 No action, shutter open
			192 - 223 Slow to fast random strobe
			224 - 255 No action, shutter open
8	8	Cyan	000 ~ 255 0% to 100%
	9	Cyan fine	000 ~ 255 0% to 100%
9	10	Magenta	000 ~ 255 0% to 100%
	11	Magenta fine	000 ~ 255 0% to 100%
10	12	Yellow	000 ~ 255 0% to 100%
	13	Yellow fine	000 ~ 255 0% to 100%
11	14	CTO	000 ~ 255 0% to 100%
	15	CTO fine	000 ~ 255 0% to 100%
12	16	Colour Wheel	000 - 000 Color off (open)
			001 - 011 Open / Color1
			012 - 022 Color1
			023 - 033 Color1 / Color2
			034 - 044 Color2
			045 - 055 Color2 / Color3
			056 - 066 Color3
			067 - 077 Color3 / Color4
			078 - 088 Color4
			089 - 099 Color4 / Color5
			100 - 110 Color5
			111 - 121 Color5 / Color6
			122 - 132 Color6
			133 - 143 Color6 / Color7
			144 - 154 Color7
			155 - 165 Color7 / Color8
			166 - 176 Color8
			177 - 188 Color8 / Open

13	17	Gobo Wheel 1	189 - 192 Open
			193 - 223 Color Wheel rot. fast -> slow, fwd
			224 - 224 Color Wheel rot. stop
			225 - 255 Color Wheel rot. slow -> fast, bwd
			000 - 013 Open
			014 - 030 Gobo 1
			031 - 047 Gobo 2
			048 - 064 Gobo 3
			065 - 081 Gobo 4
			082 - 098 Gobo 5
			099 - 115 Gobo 6
			116 - 132 Gobo 7
			133 - 159 Open
			160 - 162 Gobo Shake 1 (slow -> fast)
			163 - 165 Gobo Shake 2 (slow -> fast)
			166 - 168 Gobo Shake 3 (slow -> fast)
			169 - 171 Gobo Shake 4 (slow -> fast)
			172 - 174 Gobo Shake 5 (slow -> fast)
			175 - 177 Gobo Shake 6 (slow -> fast)
			178 - 180 Gobo Shake 7 (slow -> fast)
14	18	Gobo 1 Rotation	181 - 191 Open
			192 - 223 Gobo Wheel rotation fast -> slow, fwd
			224 - 224 Gobo Wheel rotation Stop
			225 - 255 Gobo Wheel rotation slow -> fast, bwd
15	19	Gobo1 Rotation fine	000 - 128 Gobo position 0° ... 540°
16	20	Zoom	129 - 191 Gobo rotation, fast -> slow, fwd
	21	Zoom fine	192 - 192 Gobo rotation stop
17	22	Focus	193 - 255 Gobo rotation, slow -> fast -> , bwb
18	23	Focus fine	000 - 255 Gobo indexing fine
19	24	Iris	000 - 255 Narrow to wide
			000 - 255 Narrow to wide
			000 - 255 0% to 100%
			000 - 255 0% to 100%
			000 - 191 Max. diameter to Min.diameter
20	25	Prism 1	192 - 212 Pulse opening fast to slow
			213 - 233 Pulse closing slow to fast
			234 - 254 Random effect, slow -> fast
			255 - 255 Fast opening to Fast closing
			000 - 005 Prism Off
			006 - 255 Prism 1

21	26	Prism 1 Rot	000 - 128 Prism1 position 0° ... 540°
			129 - 191 Prism1 rotation, fast -> slow, fwd
			192 - 192 Prism1 rotation Stop
			193 - 255 Prism1 rotation, slow -> fast, bwd
22	27	Prism 2	000 - 005 Prism Off
			006 - 255 Prism 2
23	28	Prism 2 Rot	000 - 128 Prism2 position 0° ... 540°
			129 - 191 Prism2 rotation, fast -> slow, fwd
			192 - 192 Prism2 rotation Stop
			193 - 255 Prism2 rotation, slow -> fast, bwd
24	29	Frost soft	000 - 255 0% to 100%
25	30	Frost heavy	000 - 255 0% to 100%
26	31	Animation	000 - 005 Animation Off
			006 - 063 Animation indexing
			064 - 094 Animation Rotation fast to slow, CW
			095 - 096 No rotation
			097 - 127 Animation Rotation slow to fast, CCW
			128 - 158 Animation Rotation slow to fast, CW to CCW
			159 - 160 No rotation
			161 - 191 Animation Snap. fast to slow, CW
			192 - 193 No rotation
			194 - 224 Animation Snap. slow to fast, CCW
			225 - 255 Animation Snap. slow to fast, CW to CCW
27	32	Blade 1A	000 - 255 0% to 100%
	33	Blade 1A fine	000 - 255 0% to 100%
28	34	Blade 1B	000 - 255 0% to 100%
	35	Blade 1B fine	000 - 255 0% to 100%
29	36	Blade 2A	000 - 255 0% to 100%
	37	Blade 2A fine	000 - 255 0% to 100%
30	38	Blade 2B	000 - 255 0% to 100%
	39	Blade 2B fine	000 - 255 0% to 100%
31	40	Blade 3A	000 - 255 0% to 100%
	41	Blade 3A fine	000 - 255 0% to 100%
32	42	Blade 3B	000 - 255 0% to 100%
	43	Blade 3B fine	000 - 255 0% to 100%
33	44	Blade 4A	000 - 255 0% to 100%
	45	Blade 4A fine	000 - 255 0% to 100%

34	46	Blade 4B	000 - 255 0% to 100%
	47	Blade 4B fine	000 - 255 0% to 100%
35	48	Blade Rotation	000 - 255 0% to 100%
	49	Blade Rotation fine	000 - 255 0% to 100%
36	50	Pan/Tilt Speed	000 - 255 Pan/Tilt Fast -> Slow
37	51	Dim Mode	000 - 020 Standard
			021 - 040 Stage
			041 - 060 TV
			061 - 080 Architectural
			081 - 100 Theatre
			101 - 255 Default to Unit Setting
38	52	Device settings	000 - 005 No function
			006 - 007 Blackout while P/T moving on
			008 - 009 Blackout while P/T moving off
			010 - 011 Blackout while wheels moving on
			012 - 013 Blackout while wheels moving off
			014 - 041 No function
			042 - 043 Invert Pan on (hold 3s)
			044 - 045 Invert Pan off (hold 3s)
			046 - 047 Invert Tilt on (hold 3s)
			048 - 049 Invert Tilt off (hold 5s)
			050 - 051 Pan Angle 540° (hold 3s)
			052 - 053 Pan Angle 630° (hold 3s)
			054 - 101 No function
			102 - 103 Fan Constant Low (hold 3s)
			104 - 105 Fan Constant Auto (hold 3s)
			106 - 107 Fan Constant High (hold 3s)
			108 - 163 No function
			164 - 165 Dimmer Curve Linear (hold 3s)
			166 - 167 Dimmer Curve Square (hold 3s)
			168 - 169 Dimmer Curve Inv-Square(hold 3s)
			170 - 171 Dimmer Curve S-Curve (hold 3s)
			172 - 221 No function
			222 - 223 Reset Pan / Tilt (hold 3s)
			224 - 233 No function
			234 - 235 Reset Head complete (hold 3s)
			236 - 237 Reset all functions (hold 3s)
			250 - 255 No function

Not bright	LED aging or damage	Replace
	Power PCB malfunction	Check/ Replace
	Loose or poor contact of the circuit	Reconnect
	PSU malfunction	Replace
Automatically turn off or dim the lights	LED aging	Replace
	Damaged cooling fan or abnormal wind speed	Replace
	Check the power output of the fan	Check/ Replace
	The temperature control switch is damaged	Replace
Gobo wheel misalignment or abnormal control	Poor contact of motor wire	Reconnect
	Corresponding motor drive board malfunction	Refixed
	Misalignment or magnetic damage between the magnetic tube and the positioning magnet	Adjust/Replace
	Motor malfunction	Replace
Weak light efficiency and uneven light spot	LED aging	Replace
	LED not centered with the lens	Adjust LED
	The optical mirror has accumulated dust or stains	Clean
	The optical mirror is damaged	Replace
Impure color	Weakening of light efficiency	Replace led PCB
	The color filter has accumulated dust or stains	Clean
	The color filter has been demolded or damaged	Replace
Gobo is unclear	The optical mirror has accumulated dust or stains	Clean
	The optical mirror is damaged	Replace

Head or base fan stops rotating	Check if the fan leads are installed properly or disconnected	Re connect
	Check if the fan is damaged	Replace
	Check if there are any other interfering objects within the operating range of the fan	Adjust
 Attention! The above analysis is for abnormal reference only. Non professionals are not allowed to disassemble and repair the machine		

